






Description Combination Exit/Emergency Light - Remote Capable

LED Sign

Incandescent Lamps

Features

- Completely Self-Contained
- Fully Automatic Operation
- Compact, Low Profile Designs in Neutral Finish
- Push to Test Switch
- 6-Volt Maintenance Free Lead Acid Battery
- Environmental Coated, Solid State Charger
- Adjustable Arms Allow Vertical or Horizontal Lamp Orientation
- 2 5.4 Watt Fully Adjustable Glare Free Lamps
- Automatic, Low Voltage Disconnect (LVD)
- Universal Transformer for 120 or 277 VAC
- Universal J-Box Mounting Plate
- Injection Molded, V-O Flame Retardant, High Impact, Thermoplastic Housing
- Integral wiring channels for ease of installation
- Charge Rate/Power on LED Indicator Light
- Rated for Damp Location
- Remote Capable Up to 2 additional remote Lamp Heads
- 2 Heads 4 Hours Operation 3 Heads - 2 Hours Operation 4 Heads - 1.5 Hours Operation



Dimension Information

L Inches	22.00
H Inches	10.00
W Inches	13.00
Depth Inches (mm)	2.75

Specifications

Input Rating Amps: .11A @120V, .06A @ 277V
Input Rating Watts: 10W @ 120V 10W @ 277V

Frequency: 60 Hz

Lamp Type: 5.4 W Incandescent Wedge Base

Voltage Rating: 120/277 Flammability Rating: UL94V-0

Battery Operation: 6 Volt 4.5 AH Lead Acid - 90 Minutes Minimum

Packaging

Box Qty 1 Master Carton Qty 6

Certifications

UL UL 924 cUL No RoHS Yes

Cat No.	LED Color	Housing	Case Qty	Each
73034	Red	White	6	
73035	Red	Black	6	
73036	Green	White	6	
73037	Green	Black	6	